

This manual is intended for users of the DA-BH1100 wall mounting bracket. It includes instructions for mounting the DA-BH1100 wall mounting bracket to a wall.




- **This bracket is intended to be used with DC-B series model of camera. Do not use it with other models of cameras.**
- **This installation should be performed by a qualified service personnel in conformance to all local codes.**
- **You may need to reinforce the wall. If the wall is not strong enough to support the camera, the camera may fall.**
- **Do not use this product for other purposes.**


Mounting

Connect your camera to the bracket as follows:


- 1 Screw the provided black plate onto the mount bracket of the camera bottom.




- 2 Screw the plate in the bracket by using the provided screws.




- 3 Connect the provided cable glands to the holes in the rear of the bracket, and screw it by using the locknuts.



- 4 Insert cables from external devices, network and power adapter into the cable glands.




- 5 Turn the cable glands clockwise to tighten the pressure fingers of the thread.



Mount the bracket to the wall as follows:

- 6 Close the top cover of the bracket and lock it.
7 Mount the bracket to the wall.
8 Turn on power.



Dimensions

Unit: mm (inch)

